

U7000 (ISL6259HRTZ) MBP 13 2012

PLUG-IN, NO BOOT STATE

AGATE	PIN 1	0V	CHGR_AGATE	
DCIN	PIN 2	16V	PPCHGR_DCIN	
ACIN	PIN 3	3.9V	CHGR_ACIN	
VFRQ	PIN 4	3.4V	CHGR_VFRQ	<IN
ICOMP	PIN 5	1.3V	CHGR_ICOMP	
CELL	PIN 6	3.4V	CHGR_CELL	
VCOMP	PIN 7	1.8V	CHGR_VCOMP	
VNEG	PIN 8	2.1V	CHGR_VNEG	
AMON	PIN 9	0.3V	CHGR_AMON	OUT>
SDA	PIN 10	3.4V	=SMBUS_CHGR_SDA	<BI>
SCL	PIN 11	3.4V	=SMBUS_CHGR_SCL	<IN
VHST	PIN 12	3.4V	=PP3V42_G3H_CHGR	
SMB_RST_N	PIN 13	3.4V	CHGR_RST_L	<IN
ACOK	PIN 14	3.4V	=CHGR_ACOK	OUT>
BMON	PIN 15	0V	CHGR_BMON	OUT>
BGATE	PIN 16	5.2V	CHGR_BGATE	
CSN	PIN 17	12.3V	CHGR_CSO_N	
CSOP	PIN 18	12.3V	CHGR_CSO_P	
VDD	PIN 19	5V	PP5V1_CHGR_VDD	
VDDP	PIN 20	5V	PP5V1_CHGR_VDDP	
LGATE	PIN 21	0.5V	CHGR_LGATE	
PGND	PIN 22	0V	GND	
PHASE	PIN 23	12.6V	CHGR_PHASE	
UGATE	PIN 24	12.6V	CHGR_UGATE	
BOOT	PIN 25	16.5V	CHGR_BOOT	
SGATE	PIN 26	16.5V	CHGR_SGATE	
CSIN	PIN 27	16.5V	CHGR_CSI_N	
CSIP	PIN 28	16.5V	CHGR_CSI_P	